arXiv:cs/0505015v4 [cs.NA] 29 Jul 2009

COMPLEX MEAN AND VARIANCE OF LINEAR REGRESSION MODEL FOR HIGH-NOISED SYSTEMS BY KRIGING

T. SUSŁO

Abstract. The aim of the paper is to derive the complex-valued least-squares estimator for bias-noise mean and variance.

1. Kriging

Let us consider a stationary random process $\epsilon = \{\epsilon_j;\ \mathbb{N}_1 \ni j \supset i = 1, \dots, n\}$ with zero mean

$$E\{\epsilon_i\} = E\{\epsilon_j\} = E\{\epsilon\} = 0$$

and the background trend $\sum_k f_{jk}\beta^k = f_{jk}\beta^k$ (some known mean function $m(j)$ with unknown regression parameters β^k, where $k = 1, 2, \dots$) then

$$V_j = \epsilon_j + m(j) = \epsilon_j + f_{jk}\beta^k \qquad \text{e.g. } j = n + 1$$

and

$$V_i = \epsilon_i + m(i) = \epsilon_i + f_{ik}\beta^k \qquad i = 1, \dots, n\ ,$$

where f_{jk} (f') is a given vector and f_{ik} (F') is a given matrix.
The unbiasedness constraint on the estimation statistics $\hat{V}_j = \omega^i_j V_i$

$$E\{V_j\} = E\{\omega^i_j V_i\}$$

produces the system of $N(k)$ equations in the n unknowns ω^i_j

$$f_{jk} = \omega^i_j f_{ik} \quad (f' = \omega' F)\ .$$

For white noise

$$E\{[\hat{\epsilon}_j - \epsilon_j]^2\} = \sigma^2 + \sigma^2 \omega^i_j \rho_{ii} \omega^i_j \quad \left(E\{[\hat{\epsilon} - \epsilon]^2\} = \sigma^2 + \sigma^2 \omega' \Lambda \omega\right)\ ,$$

where ρ_{ii} (Λ) is the identity auto-correlation matrix, the minimization constraint

$$\frac{\partial E\{[\hat{\epsilon}_j - \epsilon_j]^2\}}{\partial \omega^i_j} = 2\sigma^2 \rho_{ii} \omega^i_j + 2\sigma^2 f_{ik} \mu^k_j = 0\ ,$$

where

$$E\{[\hat{\epsilon}_j - \epsilon_j]^2\} = \sigma^2 + \sigma^2 \omega^i_j \rho_{ii} \omega^i_j + 2\sigma^2 \underbrace{(\omega^i_j f_{ik} - f_{jk})}_{0} \mu^k_j\ ,$$

let us add the n equations in the $N(k)$ unknowns μ^k_j to the system

$$\rho_{ii} \omega^i_j = -f_{ik} \mu^k_j$$

equivalent to

$$\omega^i_j = -\rho^{ii} f_{ik} \mu^k_j$$

substituting this term into the unbiased system

$$f_{kj} = f_{ki} \omega^i_j$$

we get

$$\mu_j^k = -(f_{ki}\rho^{ii}f_{ik})^{-1}f_{kj}$$

and the kriging weights

$$\omega_j^i = \rho^{ii}f_{ik}(f_{ki}\rho^{ii}f_{ik})^{-1}f_{kj} = f_{jk}(f_{ki}\rho^{ii}f_{ik})^{-1}f_{ki}\rho^{ii} \ .$$

Now, we can write the kriging estimator

$$\hat{v}_j = \omega_j^i v_i = f_{jk}\hat{\beta}^k \quad \left(\hat{v} = \omega'\mathbf{v} = f'\hat{\beta}\right) \ ,$$

where the least-squares estimator

$$\hat{\beta}^k = (f_{ki}\rho^{ii}f_{ik})^{-1}f_{ki}\rho^{ii}v_i \quad \left(\hat{\beta} = (F'\Lambda^{-1}F)^{-1}F'\Lambda^{-1}\mathbf{v}\right)$$

is the best linear unbiased estimator for $n \to \infty$

$$\lim_{n\to\infty} E\{[\hat{V}_j - f_{jk}\beta^k]^2\} = \lim_{n\to\infty} E\{[\hat{v}_j - f_{jk}\beta^k]^2\} = 0 \ ,$$

where

$$E\{[\hat{V}_j - f_{jk}\beta^k]^2\} = \sigma^2\omega_j^i\rho_{ii}\omega_j^i = -\sigma^2\omega_j^i f_{ik}\mu_j^k = -\sigma^2 f_{jk}\mu_j^k = \sigma^2 f_{jk}(f_{ki}\rho^{ii}f_{ik})^{-1}f_{kj} \ .$$

2. COMPLEX-VALUED BIAS-NOISE MEAN AND VARIANCE

Since for constant bias-noise mean ($k = 1$)

$$V_j = \epsilon_j + f_{kj}\beta^k = \epsilon_j + \beta^1$$

and

$$V_i = \epsilon_i + f_{ki}\beta^k = \epsilon_i + \beta^1 \quad i = 1, \dots, n$$

the precession of the estimation statistics can not be compared to zero value

$$E\{[\hat{V}_j - \beta^1]^2\} = \frac{\sigma^2}{n}$$

let us introduce the bias-noise mean with non-zero slope ($k = 1, 2$)

$$V_j = \epsilon_j + f_{jk}\beta^k = \epsilon_j + \beta^1 + j\beta^2$$

and

$$V_i = \epsilon_i + f_{ik}\beta^k = \epsilon_i + \beta^1 + i\beta^2 \quad i = 1, \dots, n$$

to find the best linear unbiased estimator for any $n \geq 2$

$$E\{[\hat{V}_j - f_{jk}\beta^k]^2\} = E\{[\hat{v}_j - f_{jk}\beta^k]^2\} = 0$$

we have to fulfill

$$f_{jk}(f_{ki}\rho^{ii}f_{ik})^{-1}f_{kj} = \begin{bmatrix} 1 & j \end{bmatrix} \begin{bmatrix} n & n\bar{i} \\ n\bar{i} & n\overline{i^2} \end{bmatrix}^{-1} \begin{bmatrix} 1 \\ j \end{bmatrix} = \frac{j^2 - 2m_n j + m_{sn}}{n\sigma_n^2} = 0$$

at

$$j = m_n \pm I\sigma_n$$

in

$$\hat{v}_j = \omega_j^i v_i = f_{jk}\hat{\beta}^k = \hat{\beta}^1 + j\hat{\beta}^2 = \hat{b} + j\hat{a} \ ,$$

where: $I = \sqrt{-1}$, $m_n = \bar{i} = \frac{1}{n}\sum_i i$, $m_{sn} = \overline{i^2} = \frac{1}{n}\sum_i i^2$, $\sigma_n = \sqrt{\overline{i^2} - \bar{i}^2}$; and we get simple mean

$$\hat{m} = \hat{b} + m_n\hat{a} \pm I\sigma_n\hat{a} = \overline{v_i} \pm I\sigma_n^{-1}\left(\overline{iv_i} - m_n\overline{v_i}\right)$$

and variance

$$\hat{\sigma}^2 = \omega^i v_i^2 - \hat{m}^2 \ ,$$

where

$$\omega^i v_i^2 = \overline{v_i^2} \pm I\sigma_n^{-1}\left(\overline{iv_i^2} - m_n\overline{v_i^2}\right) \ ,$$

charged by the imaginary error.

Example. Let us consider the best linear unbiased estimator of mean

$$\overline{y_i} = \Re(\hat{m}) = 6.1$$

for a test sample $y_i(x_i)$

x_i	1.7	2.1	3.9	7.2	8.6	8.5	7.3	5.1	2.8	1.8	1.6
y_i	3.2	3.9	4.9	5.3	5.5	6.2	6.5	6.9	7.5	8.3	9.4

with the real-valued standard error

$$\pm\sqrt{\frac{\overline{y_i^2} - \overline{y_i}^2}{n}} = \pm 0.5$$

and the imaginary one

$$\Im(\hat{m}) = \pm\hat{a}\sqrt{\overline{x_i^2} - \overline{x_i}^2} = \mp 0.2 \ .$$

REFERENCES

[1] F. Štulajter, *Mean squared errors of prediction by kriging in linear models with AR(1) errors*, Acta Math. Univ. Comenianae Vol. LXIII, 2(1994) 247–254.

[2] T. Susło, *Modern statistics by kriging*, arXiv:cs.NA/0609079.